

4X4 PLUS CABLE END STRIPPERS

2X2 PLUS

Warning! This tool should not be used on live electrical circuits. It is not protected against electrical shock! Always use OSHA/ANSI or other industry approved eye protection when using tools. This tool is not to be used for purposes other than intended. Read carefully and understand instructions before using this tool.

Note: This tool is designed to strip 45 Mil to 110 Mil XLPE and EPR insulations. Insure that the proper cutting head (bushing) has been selected for the wire you are using. Both tools use the same bushings.



2 X 2




4 X 4

Operating Instructions:

1. Select wire to strip.
2. Insert wire into correctly sized bushing opening on the tool.
3. Place one hand around the cable at the place where you want the tool to stop stripping.
4. With the other hand, rotate the tool around the cable, using a slight forward pressure, and continue to rotate the tool until it reaches your other hand. This will stop the tool from moving down the cable.
5. Continue rotating the tool until it stops cutting the insulation (do not reverse the turning direction). The insulation should fall away from the tool.
6. Now the tool should spin freely on the cable against your hand.
7. Remove the tool from the cable.


Position of Replacement Blades

Small Bushings



Blades are positioned fully outward

Large Bushings



Blades are positioned fully inward



SQUARE CUT: CB 6667 BLADE

Replacement Blades



CHAMFER CUT: CB 108 BLADE

WARRANTY: The Ripley Company warrants that our line of tools are free of defect and fully operable at the time of shipment. The warranty is limited to the repair or replacement of any product which proves to be defective in material or workmanship, under normal use and service.



46 Nooks Hill Road, Cromwell, CT 06416 USA ~ Phone: 800-528-8665 ~ Int'l: (01) 860-635-2200
Fax: (01) 860-635-3631 ~ E-mail: info@ripley-tools.com ~ Internet: www.ripley-tools.com



33579 rev.2
08-12-10 ff